

208/230 Volt 3 Phase

<u>HP</u>	<u>Motor's Amps</u>		<u>RPM</u>	<u>Contactor</u>	<u>Overload</u>	<u>Baldor Motor #</u>
	<u>208V</u>	<u>230V</u>				
5	14	13.2	1750	CL25	RTN1S 14.5-18	EM3218T
7.5	20.4	19.4	1770	CL04	RTN1T 17.5-22	EM3311T
7.5	18	17.2	3450	CL04	RTN1T 17.5-22	EM3219T
10	26	25	1770	CL45	RTN1V 25-32	EM3313T
10	25.6	24	3475	CL45	RTN1V 25-32	EM3312T
15	38	35	3475	CL06	RT2E 30-43	EM3314T
20	51	47	3510	CL07	RT2G 42-55	EM2514T

460 Volt 3 Phase

<u>HP</u>	<u>Motor's Amps</u>		<u>Contactor</u>	<u>Overload</u>	<u>Baldor Motor #</u>
	<u>460V</u>	<u>RPM</u>			
5	6.6	1750	CL02	RTN1N 8-12	EM3218T
7.5	9.7	1770	CL02	RTN1N 8-12	EM3311T
7.5	8.6	1770	CL02	RTN1N 8-12	EM3219T
10	12.5	1770	CL25	RT1P 10-16	EM3313T
10	12	3475	CL25	RT1P 10-16	RM3312T
15	17.5	3475	CL04	RT1T 17.5-22	EM3314T
20	23.5	3510	CL45	RTN1U 21-26	EM2514T

208/230 Volt 1 Phase

<u>HP</u>	<u>Motor's Amps</u>		<u>RPM</u>	<u>Contactor</u>	<u>Overload</u>	<u>Baldor Motor #</u>
	<u>208V</u>	<u>230V</u>				
5	25	23	1725	40amp		L-1410T
6	27	26	1725	40amp		36H611X288G1
7.5	33	31	1725	60amp		L-1510T
7.5	33	31	3450	60amp		L-1509T
10	48	46	3450	60amp		L-1511T